



Standard Test Method for Determining Current Carrying Capacity of a Membrane Switch Circuit¹

This standard is issued under the fixed designation F1681; the number immediately following the designation indicates the year of original adoption or, in the case of revision, the year of last revision. A number in parentheses indicates the year of last reapproval. A superscript epsilon (ϵ) indicates an editorial change since the last revision or reapproval.

1. Scope

1.1 This test method covers the determination of the current carrying capacity of a conductor as part of a membrane switch.

1.2 This test method may be used to test a circuit to destruction, that is, to determine its maximum current carrying capacity, or it may be used to test the ability of a circuit to withstand a desired current level.

1.3 This test method applies only to static conditions, and does not apply to contact closure cycling of a membrane switch under current load (test method forthcoming).

1.4 *This standard does not purport to address all of the safety concerns, if any, associated with its use. It is the responsibility of the user of this standard to establish appropriate safety and health practices and determine the applicability of regulatory limitations prior to use.*

2. Referenced Documents

2.1 *ASTM Standards:*²

F1578 Test Method for Contact Closure Cycling of a Membrane Switch

F1680 Test Method for Determining Circuit Resistance of a Membrane Switch

3. Terminology

3.1 *Definitions:*

3.1.1 *conductor resistance*—the measured electrical resistance through a circuit loop between two test points.

3.1.2 *Discussion*—When a switch is included in that loop, it shall be "closed" in accordance with Test Method **F1680**.

3.1.3 *current carrying capacity (CCC)*—the maximum level of electrical current that a circuit can conduct without sustaining damage.

¹ This test method is under the jurisdiction of ASTM Committee **F01** on Electronics and is the direct responsibility of Subcommittee **F01.18** on Membrane Switches.

Current edition approved Jan. 1, 2014. Published January 2014. Originally approved in 1996. Last previous edition approved in 2007 as F1681-07a. DOI: 10.1520/F1681-14.

² For referenced ASTM standards, visit the ASTM website, www.astm.org, or contact ASTM Customer Service at service@astm.org. For *Annual Book of ASTM Standards* volume information, refer to the standard's Document Summary page on the ASTM website.

3.1.4 *membrane switch*—a momentary switching device in which at least one contact is on, or made of, a flexible substrate.

3.1.5 *power capacity*—electrical power is defined as current $\times$ voltage = $V \times I$ (watts).

3.1.6 *test points*—two preselected conductive points in a circuit loop, possibly including a switch.

4. Significance and Use

4.1 Current carrying capacity is used by designers and manufacturers of electronic interface circuitry to ensure that the membrane switch can reliably handle the loads occurring in normal use and under extreme circumstances. A thorough understanding of CCC allows manufacturers to take it into account when developing design rules for membrane switches.

4.2 Failures due to exceeding the CCC of a circuit may take the form of a significant change in conductor resistance, insulation breakdown (shorts), or conductor breakdown (opens).

4.3 Since a number of design parameters, such as trace width, ink film thickness, and heat transfer (mounting substrates, active cooling such as fans) affect the final test results, any conclusions should only be applied to specific designs, rather than to a general combination of materials.

4.4 Current carrying capacity tests may be destructive and units that have been tested should be considered unreliable for future use.

4.5 Current carrying capacity may be significantly different for static loads and dynamic (that is, cycling) loads. Failure modes are also generally different.

4.6 The use of a thermocouple to monitor the temperature of the UUT may be helpful to monitor the progress of the test.

4.7 Initial expected starting current should be calculated in advance to prevent damage to test equipment.

5. Interferences

5.1 The following parameters may affect the results of this test:

5.1.1 Temperature,

5.1.2 Relative humidity,