

Fibre optic communication system design guides –
Part 10: Characterization of the quality of optical vector-modulated signals
with the error vector magnitude

CORRIGENDUM 1

4.2 Normalization of the measured data

Replace the existing text of the second paragraph by the following new text:

The normalization factor α is chosen to match the measured vectors to the reference by first finding the value of a scaling factor β for the reference vectors that minimizes the corresponding unnormalized EVM_{rms} without changing the distribution of the measured vectors. Then the inverse of β is used as α to scale the measured vectors to the normalized reference. For this purpose, the unnormalized EVM_{rms} is expressed as

$$U = \sqrt{\frac{1}{N} \sum_{n=1}^N \left| \beta \times \mathbf{s}_{\text{ref}}^{r(n)} - \mathbf{s}_{\text{meas}}(n) \right|^2} \quad (6)$$

where $\mathbf{s}_{\text{meas}}(n) = \begin{pmatrix} I_{\text{meas}}(n) \\ Q_{\text{meas}}(n) \end{pmatrix}$

The value of β that gives minimum U is determined by solving

$$\frac{\partial U}{\partial \beta} = 0 \quad (7)$$

leading to

$$\alpha = \frac{1}{\beta} = \frac{\sum_{n=1}^N \left(I_{\text{ref}}^{r(n)2} + Q_{\text{ref}}^{r(n)2} \right)}{\sum_{n=1}^N \left(I_{\text{ref}}^{r(n)} \times I_{\text{meas}}(n) + Q_{\text{ref}}^{r(n)} \times Q_{\text{meas}}(n) \right)} \quad (8)$$